





Terminal	
NO	SYMBOL
1	/CS1
2	/RST
3	A0
4	/WR
5	/RD
6	D0
7	D1
8	D2
9	D3
10	D4
11	D5
12	D6
13	D7
14	VDD
15	VSS
16	V0
17	XV0
18	VG
19	NC
20	ESD



Panel Wiring Details  
Scale=free



DOT DETAIL  
SCALE 5:1



Backlight Circuit  
Scale=free

*1. LCD Display Type	FSTN,Transflective,Positive		
*2. Viewing Direction	6H	*6. Storage Temp	-40°C~80°C
*3. LCD Driver Mode	1/64Duty,1/9Bias	*7. Driver IC	ST7567
*4. Operating Voltage	3.3V	*8. Backlight	WHITE V <sub>F</sub> =3.0V I <sub>F</sub> =45mA
*5. Operating Temp	-30°C~80°C	*9. RDHS	

## HOT DISPLAY

Dwg Title: HTG12864T01A-MCU8080

Dwg No: \_\_\_\_\_ Ver: A/0

Scale: 1:1    Unit: mm    Tol: ±0.3

Drawn: \_\_\_\_\_ Checked: \_\_\_\_\_ Date: 2022-09-20